## Arlington's MB8 Mounting Block...





- Supports Floodlights, Smoke Detectors...even Fans or Fixtures in excess of 35 lbs!
- For Interior or Exterior use
- ▼ UL/CSA Listed for Ceiling Fan & Fixture support

PATENT PENDING ©1998 Arlington Industries, Inc.

## COULTING BOX



Mounts Fans, Fixtures, and More directly to Ceiling Joist for EXTRA-SECURE Support!

- It's a Ceiling **Medallion and** Electrical Box -Combined!
- For Supporting Ceiling Fans, Light Fixtures, Flood Lights, Smoke Detectors. - ANY fixture needing a Safe & Strong Installation
- Duse as a Decorative Medallion tool



## For Ceiling Fixtures & Fans

Locate the ceiling joist using a stud finder or similar device.

Drill a hole approximately 1/2" in diameter, in the ceiling next to the joist.

## There's no need to cut the ceiling drywall!


Remove desired knockout. Insert the cable connector into the opening, and pull the NM cable through the connector.



Using the #8 x 1-1/2" wood screws (provided), mount the MB8 to the joist (through the ceiling).

CATALOG NUMBER	UPC/DCI/NAED MFG #01 8997	DESCRIPTION	UNIT PKG	STD PKG
MB8	42330 V	8" Medallion with Built-in Box	1 <	10

Each MB8 comes with (2) #10 x 3" wood screws, (1) #8 x 1-1/2" wood screw, (2) lock washers, and (1) NM94 non-metallic cable connector.



Install the fixture or fan mounting bar (provided with fixture or fan) directly to the joist with the (2) #10 x 3" wood screws and lock washers provided.

Wire the fixture or fan following the instructions included with the product.

Comply with all local electrical codes and regulations.



Made of UV Rated Material • For Indoor or Outdoor Use

Arlington 1 Stauffer Industrial Park Scranton, PA 18517

800/233-4717 · FAX 717/562-0646