## Arlington /

## **Siding Mounting Kits with Built-in Box**



8141



8141DBL

For smooth vertical mounting of light fixtures on all siding types. Kit includes mounting block with built-in electrical box, NM cable connector, and 4 screws. Paintable, UV rated plastic for long outdoor life.

## **FEATURES AND BENEFITS**

- Mounts light fixtures on all siding types, including T-111, HardiePlank® Lap Siding, and flat surfaces
- Fast and easy to install after siding is up
- Textured, paintable surface
- NM cable connector included
- Built-in electrical box design ensures UL listed installation

| CATALOG<br>NUMBER | UPC/DCI/NAED<br>MFG #018997 | SIDING<br>TYPE                    | UNIT<br>PKG | STD<br>PKG | DIM<br>A                   | DIM<br>B | DIM<br>C |
|-------------------|-----------------------------|-----------------------------------|-------------|------------|----------------------------|----------|----------|
| 8131              | 08131                       | 1/4" & 5/16"<br>Siding & Shingles | 1           | 10         | 4" Diameter<br>X 1/2" Deep | 6.625    | 6.625    |
| 8141              | 10751                       | 1/2" Lap                          | 1           | 10         | 4" Diameter<br>X 1/2" Deep | 6.625    | 6.625    |
| 8141DBL           | 54524                       | 1/2" Lap Double                   | 1           | 10         | 4" Diameter<br>X 1/2" Deep | 6.900    | 10.200   |
| 8151              | 10753                       | 5/8" Lap                          | 1           | 10         | 4" Diameter<br>X 1/2" Deep | 6.625    | 6.625    |
| 8161              | 08161                       | Flat Surfaces                     | 1           | 10         | 4" Diameter<br>X 1/2" Deep | 6.625    | 6.625    |
| 8171              | 10757                       | Dutch Lap                         | 1           | 10         | 4" Diameter<br>X 1/2" Deep | 6.625    | 6.625    |

Add suffix "GC" to Catalog # when ordering in Canada to include grounding clip, for example 8141GC. PATENTED.



## **INSTALLATION INSTRUCTIONS** for Sidina



Select location for light fixture and caulk opening around cable.



Remove knockout from electrical box and insert cable connector. Push cable through connector and position mounting block onto siding.



Secure mounting block with provided screws. Install fixture per manufacturer's instructions.





